

**APM32E103xE**

**Errata Sheet**

**Version: V 2.0**

## Contents


1 Introduction .....	2
2 Product Version and Silk Screen Printing Instructions .....	3
3 Errata List.....	4
4 GPIO .....	5
4.1 GPIO output.....	5
4.2 USART3 and FSMC remapping .....	5
5 Clock .....	6
5.1 Precautions for obtaining accurate RTC calibration clock output from PC13.....	6
6 System .....	7
6.1 PWR sleep mode.....	7
6.2 FPU functions .....	7
6.3 Low-power mode .....	7
7 USBD/CAN.....	8
7.1 Combined use of USBD/CAN.....	8
7.2 CAN2_IO remapping .....	8
8 Revision history.....	9

## 1 Introduction

This manual mainly introduces the limitations of the APM32E103xE series products during use. If you encounter the application scenarios described in the manual during the use of the product, please use the product according to the solutions provided in the manual; if no solution is provided, please avoid this application scenario.

## 2 Product Version and Silk Screen Printing Instructions

Figure 1 Product Version and Silk Screen Printing Instructions



### 3 Errata List

Table 1 Errata List

Category	Introduction	Product version	
		A2	A2X
GPIO	GPIO output	•	•
	USART3 and FSMC remapping	•	•
Clock	Precautions for obtaining accurate RTC calibration clock output from PC13	•	•
System	PWR sleep mode	•	•
	FPU functions	•	•
	Low-power mode	•	•
USB/CAN	Combined use of USB/CAN	•	•
	CAN2_IO remapping	•	•

Note: "•" indicates that this errata description is involved in this version; the 'X' indicates that it is not involved in this version.

## 4 GPIO

### 4.1 GPIO output

#### Problem description

When the GPIO port is configured as multiplexing push-pull output, the output voltage may be affected by external interference and is unable to output accurate levels; when configured as floating input to read the external I/O input values, it may be affected by external interference and is unable to read accurate values.

#### Solutions

When configured as multiplexing push-pull output, connect an external pull-up resistor; when configured as floating input, connect an internal pull-up resistor externally or configure it as a pull-up input.

### 4.2 USART3 and FSMC remapping

#### Problem description

USART\_USART3 remapping PD8 and PD9 pins conflicts with FSMC clock. Specifically: when remapping PD8 and PD9 as serial pins, enable FSMC clock but the serial communication cannot be used normally.

#### Solutions

Choose either of the following solutions:

- Use partial remapping function or default configuration of USART3.
- When USART3\_TX is remapped to PD8 as a serial port pin, disable the SMC function.

## 5 Clock

### 5.1 Precautions for obtaining accurate RTC calibration clock output from PC13

#### Problem description

When LSECLK is used as the clock source for RTC, after the ready flag bit of the external low-speed clock is set to 1, immediately configure RTC and PC13 to output the calibration clock signal. At this time, the output calibration clock may be delayed, and the output calibration clock will be accurate only after a period of time.

#### Solutions

When the ready flag bit of the external low-speed clock is set to 1, configure the PC13 to output the calibration clock signal after delay for a period of time, or wait for a period of time before measuring the calibration signal. It is important to note that the waiting time may vary with the parameters, temperature, and voltage differences of the crystal oscillator. The recommended delay reference time is 1s.

## 6 System

### 6.1 PWR sleep mode

#### Problem description

The PWR sleep mode `_WEF()` instruction is invalid and cannot enter the low-power mode.

#### Solutions

Choose either of the following solutions:

- It can be executed normally after it is reset through the reset pin.
- Set in the download interface of Keil (set the reset and run).
- The second WFE instruction can be executed normally.
- Modify the program, and use 1 WFI rather than WFE.

### 6.2 FPU functions

#### Problem description

The larger the input value of FPU is, the higher the probability of occurrence of errors is.

#### Solutions

Suggest controlling the FPU input value within  $\pm 3\pi$ . It is important to note that the operation acceleration effect of FPU only applies to the functions in the LIB library, and it has no significant acceleration effect on other operations such as +, -, ×, ÷, and matrix permutation.

### 6.3 Low-power mode

#### Problem description

When the FSMC clock is enabled, the power consumption is high when entering the Standby and Stop low-power modes.

#### Solutions

First turn off the FSMC clock, and then enter the Standby and Stop low-power modes.



## 7 USBD/CAN

### 7.1 Combined use of USBD/CAN

#### Problem description

USBD1 and CAN2 can be used simultaneously, USBD2 and CAN1 can be used simultaneously, USBD1 and USBD2 cannot be used simultaneously, and CAN1 and CAN2 can be used simultaneously.

#### Solutions

Use according to the recommendations of *Datasheet* and *User Manual*.

### 7.2 CAN2\_IO remapping

#### Problem description

If CAN2 uses remapping pins (e.g., I/O initialization) and then performs other peripheral remapping operation, CAN2 will fail to remap.

#### Solutions

Perform CAN2 remapping (e.g., I/O initialization) operation after all peripheral remapping operations.

## 8 Revision history

Table2 Document Revision History

Date	Version	Revision History
August 2024	1.0	New edition

# Statement

This document is formulated and published by Geehy Semiconductor Co., Ltd. (hereinafter referred to as “Geehy”). The contents in this document are protected by laws and regulations of trademark, copyright and software copyright. Geehy reserves the right to make corrections and modifications to this document at any time. Read this document carefully before using Geehy products. Once you use the Geehy product, it means that you (hereinafter referred to as the “users”) have known and accepted all the contents of this document. Users shall use the Geehy product in accordance with relevant laws and regulations and the requirements of this document.

## 1. Ownership

This document can only be used in connection with the corresponding chip products or software products provided by Geehy. Without the prior permission of Geehy, no unit or individual may copy, transcribe, modify, edit or disseminate all or part of the contents of this document for any reason or in any form.

The “极海” or “Geehy” words or graphics with “®” or “TM” in this document are trademarks of Geehy. Other product or service names displayed on Geehy products are the property of their respective owners.

## 2. No Intellectual Property License

Geehy owns all rights, ownership and intellectual property rights involved in this document.

Geehy shall not be deemed to grant the license or right of any intellectual property to users explicitly or implicitly due to the sale or distribution of Geehy products or this document.

If any third party’s products, services or intellectual property are involved in this document, it shall not be deemed that Geehy authorizes users to use the aforesaid third party’s products, services or intellectual property. Any information regarding the application of the product, Geehy hereby disclaims any and all warranties and liabilities of any kind, including without limitation warranties of non-infringement of intellectual property rights of any third party, unless otherwise agreed in sales order or sales contract.

## 3. Version Update

Users can obtain the latest document of the corresponding models when ordering Geehy products.

If the contents in this document are inconsistent with Geehy products, the agreement in the sales order or the sales contract shall prevail.

#### 4. Information Reliability

The relevant data in this document are obtained from batch test by Geehy Laboratory or cooperative third-party testing organization. However, clerical errors in correction or errors caused by differences in testing environment may occur inevitably. Therefore, users should understand that Geehy does not bear any responsibility for such errors that may occur in this document. The relevant data in this document are only used to guide users as performance parameter reference and do not constitute Geehy's guarantee for any product performance.

Users shall select appropriate Geehy products according to their own needs, and effectively verify and test the applicability of Geehy products to confirm that Geehy products meet their own needs, corresponding standards, safety or other reliability requirements. If losses are caused to users due to user's failure to fully verify and test Geehy products, Geehy will not bear any responsibility.

#### 5. Legality

USERS SHALL ABIDE BY ALL APPLICABLE LOCAL LAWS AND REGULATIONS WHEN USING THIS DOCUMENT AND THE MATCHING GEEHY PRODUCTS. USERS SHALL UNDERSTAND THAT THE PRODUCTS MAY BE RESTRICTED BY THE EXPORT, RE-EXPORT OR OTHER LAWS OF THE COUNTRIES OF THE PRODUCTS SUPPLIERS, GEEHY, GEEHY DISTRIBUTORS AND USERS. USERS (ON BEHALF OR ITSELF, SUBSIDIARIES AND AFFILIATED ENTERPRISES) SHALL AGREE AND PROMISE TO ABIDE BY ALL APPLICABLE LAWS AND REGULATIONS ON THE EXPORT AND RE-EXPORT OF GEEHY PRODUCTS AND/OR TECHNOLOGIES AND DIRECT PRODUCTS.

#### 6. Disclaimer of Warranty

THIS DOCUMENT IS PROVIDED BY GEEHY "AS IS" AND THERE IS NO WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, TO THE EXTENT PERMITTED BY APPLICABLE LAW.

GEEHY'S PRODUCTS ARE NOT DESIGNED, AUTHORIZED, OR WARRANTED FOR USE AS CRITICAL COMPONENTS IN MILITARY, LIFE-SUPPORT, POLLUTION CONTROL, OR HAZARDOUS SUBSTANCES MANAGEMENT SYSTEMS, NOR WHERE FAILURE COULD RESULT IN INJURY, DEATH, PROPERTY OR ENVIRONMENTAL DAMAGE.

IF THE PRODUCT IS NOT LABELED AS "AUTOMOTIVE GRADE," IT SHOULD NOT BE CONSIDERED SUITABLE FOR AUTOMOTIVE APPLICATIONS. GEEHY ASSUMES NO LIABILITY FOR THE USE BEYOND ITS SPECIFICATIONS OR GUIDELINES.

THE USER SHOULD ENSURE THAT THE APPLICATION OF THE PRODUCTS COMPLIES

WITH ALL RELEVANT STANDARDS, INCLUDING BUT NOT LIMITED TO SAFETY, INFORMATION SECURITY, AND ENVIRONMENTAL REQUIREMENTS. THE USER ASSUMES FULL RESPONSIBILITY FOR THE SELECTION AND USE OF GEEHY PRODUCTS. GEEHY WILL BEAR NO RESPONSIBILITY FOR ANY DISPUTES ARISING FROM THE SUBSEQUENT DESIGN OR USE BY USERS.

#### 7. Limitation of Liability

IN NO EVENT, UNLESS REQUIRED BY APPLICABLE LAW OR AGREED TO IN WRITING WILL GEEHY OR ANY OTHER PARTY WHO PROVIDES THE DOCUMENT AND PRODUCTS "AS IS", BE LIABLE FOR DAMAGES, INCLUDING ANY GENERAL, SPECIAL, DIRECT, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR INABILITY TO USE THE DOCUMENT AND PRODUCTS (INCLUDING BUT NOT LIMITED TO LOSSES OF DATA OR DATA BEING RENDERED INACCURATE OR LOSSES SUSTAINED BY USERS OR THIRD PARTIES). THIS COVERS POTENTIAL DAMAGES TO PERSONAL SAFETY, PROPERTY, OR THE ENVIRONMENT, FOR WHICH GEEHY WILL NOT BE RESPONSIBLE.

#### 8. Scope of Application

The information in this document replaces the information provided in all previous versions of the document.

© 2024 Geehy Semiconductor Co., Ltd. - All Rights Reserved