

APM32F107xE

Errata Sheet

Version: V 2.0

Contents


1 Introduction	2
2 Product Version and Silk Screen Printing Instructions	3
3 Errata List.....	4
4 GPIO	5
4.1 GPIO output.....	5
5 System	6
5.1 PWR sleep mode.....	6
6 USB/CAN	7
6.1 LS Host Mode of USB_OTG_FS Module.....	7
6.2 RX communication of CAN2.....	7
7 Revision history.....	8

1 Introduction

This manual mainly introduces the limitations of the APM32F107xE series products during use. If you encounter the application scenarios described in the manual during the use of the product, please use the product according to the solutions provided in the manual; if no solution is provided, please avoid this application scenario.

2 Product Version and Silk Screen Printing Instructions

Figure 1 Product Version and Silk Screen Printing Instructions



3 Errata List

Table 1 Errata List

Category	Introduction	Product version
		A1
GPIO	GPIO output	•
System	PWR sleep mode	•
USB/CAN	LS host mode of USB_OTG_FS module	•
	RX communication of CAN2	•

Note: "•" indicates that this errata description is involved in this version; the 'X' indicates that it is not involved in this version.

4 GPIO

4.1 GPIO output

Problem description

When the GPIO port is configured as multiplexing push-pull output, the output voltage may be affected by external interference and is unable to output accurate levels; when configured as floating input to read the external I/O input values, it may be affected by external interference and is unable to read accurate values.

Solutions

When configured as multiplexing push-pull output, connect an external pull-up resistor; when configured as floating input, connect an internal pull-up resistor externally or configure it as a pull-up input.

5 System

5.1 PWR sleep mode

Problem description

The PWR sleep mode_WEF() instruction is invalid and cannot enter the low-power mode.

Solutions

Choose either of the following solutions:

- It can be executed normally after it is reset through the reset pin.
- Set in the download interface of Keil (set the reset and run).
- The second WFE instruction can be executed normally.
- Modify the program, and use 1 WFI rather than WFE.

6 USB/CAN

6.1 LS Host Mode of USB_OTG_FS Module

Problem description

When the USB_OTG_FS module is configured as LS host mode, the eye diagram of the 5m line test is not perfect, the eye diagram of the 1m line test at 3.0V is not perfect, and the test results of both 1m and 5m lines at 2.7V are abnormal.

Solutions

It can be corrected and improved by adjusting the off-chip series resistance. For example, in case of overshoot, increase the resistance, and if the rise and fall time is slow, reduce the resistance. The test shows that, in FS mode, the off-chip resistance is 22 Ω ; in LS mode, an off-chip resistance is 16 Ω , and a good eye diagram that can pass the test certification can be obtained.

6.2 RX communication of CAN2

Problem description

After the PB5 pin is remapped to the RX function of CAN2, when it is configured as multiplexing push-pull output, communication is impossible.

Solutions

It is suggested that PB5 should be configured as pull-up input, pull-down input or floating input after it is remapped to the RX function of CAN2.

7 Revision history

Table2 Document Revision History

Date	Version	Revision History
August 2024	1.0	New edition

Statement

This document is formulated and published by Geehy Semiconductor Co., Ltd. (hereinafter referred to as “Geehy”). The contents in this document are protected by laws and regulations of trademark, copyright and software copyright. Geehy reserves the right to make corrections and modifications to this document at any time. Read this document carefully before using Geehy products. Once you use the Geehy product, it means that you (hereinafter referred to as the “users”) have known and accepted all the contents of this document. Users shall use the Geehy product in accordance with relevant laws and regulations and the requirements of this document.

1. Ownership

This document can only be used in connection with the corresponding chip products or software products provided by Geehy. Without the prior permission of Geehy, no unit or individual may copy, transcribe, modify, edit or disseminate all or part of the contents of this document for any reason or in any form.

The “极海” or “Geehy” words or graphics with “®” or “TM” in this document are trademarks of Geehy. Other product or service names displayed on Geehy products are the property of their respective owners.

2. No Intellectual Property License

Geehy owns all rights, ownership and intellectual property rights involved in this document.

Geehy shall not be deemed to grant the license or right of any intellectual property to users explicitly or implicitly due to the sale or distribution of Geehy products or this document.

If any third party’s products, services or intellectual property are involved in this document, it shall not be deemed that Geehy authorizes users to use the aforesaid third party’s products, services or intellectual property. Any information regarding the application of the product, Geehy hereby disclaims any and all warranties and liabilities of any kind, including without limitation warranties of non-infringement of intellectual property rights of any third party, unless otherwise agreed in sales order or sales contract.

3. Version Update

Users can obtain the latest document of the corresponding models when ordering Geehy products.

If the contents in this document are inconsistent with Geehy products, the agreement in the sales order or the sales contract shall prevail.

4. Information Reliability

The relevant data in this document are obtained from batch test by Geehy Laboratory or cooperative third-party testing organization. However, clerical errors in correction or errors caused by differences in testing environment may occur inevitably. Therefore, users should understand that Geehy does not bear any responsibility for such errors that may occur in this document. The relevant data in this document are only used to guide users as performance parameter reference and do not constitute Geehy's guarantee for any product performance.

Users shall select appropriate Geehy products according to their own needs, and effectively verify and test the applicability of Geehy products to confirm that Geehy products meet their own needs, corresponding standards, safety or other reliability requirements. If losses are caused to users due to user's failure to fully verify and test Geehy products, Geehy will not bear any responsibility.

5. Legality

USERS SHALL ABIDE BY ALL APPLICABLE LOCAL LAWS AND REGULATIONS WHEN USING THIS DOCUMENT AND THE MATCHING GEEHY PRODUCTS. USERS SHALL UNDERSTAND THAT THE PRODUCTS MAY BE RESTRICTED BY THE EXPORT, RE-EXPORT OR OTHER LAWS OF THE COUNTRIES OF THE PRODUCTS SUPPLIERS, GEEHY, GEEHY DISTRIBUTORS AND USERS. USERS (ON BEHALF OR ITSELF, SUBSIDIARIES AND AFFILIATED ENTERPRISES) SHALL AGREE AND PROMISE TO ABIDE BY ALL APPLICABLE LAWS AND REGULATIONS ON THE EXPORT AND RE-EXPORT OF GEEHY PRODUCTS AND/OR TECHNOLOGIES AND DIRECT PRODUCTS.

6. Disclaimer of Warranty

THIS DOCUMENT IS PROVIDED BY GEEHY "AS IS" AND THERE IS NO WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, TO THE EXTENT PERMITTED BY APPLICABLE LAW.

GEEHY'S PRODUCTS ARE NOT DESIGNED, AUTHORIZED, OR WARRANTED FOR USE AS CRITICAL COMPONENTS IN MILITARY, LIFE-SUPPORT, POLLUTION CONTROL, OR HAZARDOUS SUBSTANCES MANAGEMENT SYSTEMS, NOR WHERE FAILURE COULD RESULT IN INJURY, DEATH, PROPERTY OR ENVIRONMENTAL DAMAGE.

IF THE PRODUCT IS NOT LABELED AS "AUTOMOTIVE GRADE," IT SHOULD NOT BE CONSIDERED SUITABLE FOR AUTOMOTIVE APPLICATIONS. GEEHY ASSUMES NO LIABILITY FOR THE USE BEYOND ITS SPECIFICATIONS OR GUIDELINES.

THE USER SHOULD ENSURE THAT THE APPLICATION OF THE PRODUCTS COMPLIES

WITH ALL RELEVANT STANDARDS, INCLUDING BUT NOT LIMITED TO SAFETY, INFORMATION SECURITY, AND ENVIRONMENTAL REQUIREMENTS. THE USER ASSUMES FULL RESPONSIBILITY FOR THE SELECTION AND USE OF GEEHY PRODUCTS. GEEHY WILL BEAR NO RESPONSIBILITY FOR ANY DISPUTES ARISING FROM THE SUBSEQUENT DESIGN OR USE BY USERS.

7. Limitation of Liability

IN NO EVENT, UNLESS REQUIRED BY APPLICABLE LAW OR AGREED TO IN WRITING WILL GEEHY OR ANY OTHER PARTY WHO PROVIDES THE DOCUMENT AND PRODUCTS "AS IS", BE LIABLE FOR DAMAGES, INCLUDING ANY GENERAL, SPECIAL, DIRECT, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR INABILITY TO USE THE DOCUMENT AND PRODUCTS (INCLUDING BUT NOT LIMITED TO LOSSES OF DATA OR DATA BEING RENDERED INACCURATE OR LOSSES SUSTAINED BY USERS OR THIRD PARTIES). THIS COVERS POTENTIAL DAMAGES TO PERSONAL SAFETY, PROPERTY, OR THE ENVIRONMENT, FOR WHICH GEEHY WILL NOT BE RESPONSIBLE.

8. Scope of Application

The information in this document replaces the information provided in all previous versions of the document.

© 2024 Geehy Semiconductor Co., Ltd. - All Rights Reserved